

STM23Q-3RE

NEMA 23 Integrated Drive+Motor w/ Q Programming & Encoder



Product Features

- Sophisticated current control
- Anti-resonance
- Torque ripple smoothing
- Microstep emulation
- Q programming mode for stand-alone control
- Capable of all "S" control modes
- RS-485 port for programming and communications
- Built-in incremental encoder



Description

The STM23Q-3RE integrated stepper is a drive+motor unit, fusing a NEMA 23 step motor and a sophisticated 5.0 A/phase (peak-of-sine) stepper drive into a single device. Power to the drive, located at the rear of the motor, must be supplied by an external DC supply. See Related and Recommended Products below for compatible 24 and 48 volt DC [power supplies](#).

The STM23Q-3RE integrated stepper can operate in all of the same control modes as the S option, plus the ability to run a Q program stored in non-volatile memory. Q programs are created using Applied Motion's [Q Programmer™](#) software, which provides powerful commands for motion, I/O, conditional processing, multi-tasking, math functions, and more. All STM23 units are setup and configured using Applied Motion's [ST Configurator™](#) software.

An integral 1000-line (4000 count/rev) incremental encoder is housed inside the same enclosure as the drive electronics, providing protection from dust and debris. The integration of the encoder means the STM23Q-3RE can perform special functions not available otherwise. Stall Detection notifies the system as soon as the required torque is too great for the motor, which results in a loss of synchronization between the rotor and stator, also known as stalling. Stall Prevention actually prevents stalling of the step motor by dynamically adjusting motor speed to maintain synchronization of the rotor to the stator under all conditions. This unique feature allows step motors to operate in a much broader range of applications than previously available to step motors, such as torque-control applications. The Stall Prevention feature also performs static position maintenance, which maintains the position of the motor shaft when at rest.

Each STM23 integrated stepper comes with 3 digital inputs, 1 digital output, and 1 analog input. The digital inputs accept signals of 5-24 VDC and can be used for connecting pulse & direction signals, end-of-travel limit switches, jog switches, quadrature encoder signals, PLC outputs, sensors, or many other signal types. The digital output can be connected to PLC inputs, counters, lights, relays, or other devices. The analog input accepts 0-5 VDC signals and can be used for velocity and position control.

The STM23Q-3RE comes with an RS-485 port for programming and serial communications.

Specifications

Part Number	STM23Q-3RE
Supply Voltage	12-70 VDC
Supply Voltage Type	DC
Control Modes	<ul style="list-style-type: none"> • Streaming Commands • Analog Positioning • Encoder Following • Q Programming
Communication Ports	<ul style="list-style-type: none"> • RS-485
Encoder Feedback	Yes
Step Resolution	<ul style="list-style-type: none"> • Full • Half • Microstepping • Microstep Emulation
Idle Current Reduction	0-90%
Setup Method	Software setup
Digital Inputs	3
Digital Outputs	1
Analog Inputs	1 single-ended
Circuit Protection	<ul style="list-style-type: none"> • Short circuit • Over-voltage • Under-voltage • Over-temp
Status LEDs	1 red, 1 green
Frame Size	NEMA 23
Holding Torque	210 oz-in
Step Angle	1.8 deg
Rotor Inertia	6.51E-03 oz-in-sec ²
Length	4.50 inches
Weight	42 oz
Operating Temperature Range	0 to 85 °C
Ambient Temperature Range	0 to 40 °C
Ambient Humidity	90% max, non-condensing
Insulation Class	Class B (130 °C)
Maximum Radial Load	NA
Maximum Thrust Load	NA
Shaft Run Out	NA
Radial Play	NA
End Play	NA
Perpendicularity	NA